

Corrections to

**Information technology—
Telecommunications and information exchange between systems—
Local and metropolitan area networks—
Specific requirements—**

Part 3: Carrier sense multiple access with collision detection (CSMA/CD) access method and physical layer specifications

Sponsor

LAN/MAN Standards Committee

of the

IEEE Computer Society

Correction Sheet

Issued 29 June 2004

Copyright © 2004 by the Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 2004. Printed in the United States of America.

This correction sheet may be freely reproduced and distributed in order to maintain the utility and currency of the underlying Standard. This correction sheet may not be sold, licensed or otherwise distributed for any commercial purposes whatsoever. The content of this correction sheet may not be modified.

IEEE Std 802.3-2002 Section 3: page 50: subclause 36.2.5.1.3 Variables.

cgbad

Alias for the following terms: ((rx_code-group ∈ /INVALID/) + (rx_code-group = /COMMA/
*rx_even=TRUE)) * PMA_UNITDATA.indicate

should read

cgbad

Alias for the following terms: ((rx_code-group ∈ /INVALID/) + (rx_code-group = /COMMA/
*rx_even=TRUE)) * PMA_UNITDATA.indicate

IEEE Std 802.3-2002 Section 3: page 50: subclause 36.2.5.1.3 Variables.

cggood

Alias for the following terms: !((rx_code-group ∈ /INVALID/) + (rx_code-group = /COMMA/
*rx_even=TRUE)) * PMA_UNITDATA.indicate

should read

cggood

Alias for the following terms: !((rx_code-group ∈ /INVALID/) + (rx_code-group = /COMMA/
*rx_even=TRUE)) * PMA_UNITDATA.indicate

IEEE Std 802.3-2002 Section 3: page 54: subclause 36.2.5.1.4 Functions.

VOID(x)

x ∈ /D/, /T/, /R/, /K28.5/. Substitutes /V/ on a per code-group basis as requested by the GMII.

should read

VOID(x)

x ∈ /D/, /T/, /R/, /K28.5/. Substitutes /V/ on a per code-group basis as requested by the GMII.

IEEE Std 802.3-2002 Section 3: page 360: 40C.1 State variables.**Delete the following variable from 40C.1:**

1000T_capable

This variable is used merely to show the local device is 1000Base-T capable. It is shown to illustrate the path that a non-1000Base-T device would take within the auto negotiation mechanism.

Insert the following variable in 40C.1 (this should be inserted in alphabetical order):

desire_1000T_adv

The local device desires a 1000BASE-T link.

Values: true; bit 9.8 or 9.9 do not contain a logic zero.
false; bits 9.8 and 9.9 both contain a logic zero.

**IEEE Std 802.3-2002 Section 3: page 363: 40C-2 Auto-Negotiation Transmit state diagram
add on for 1000BASE-T.**

Change note 3 of Figure 40C-2

3—(Flp_Link_Good_Check) This is shown for illustration only. This state is from the Auto-Negotiation arbitration state diagram and indicates the conclusion of pages being sent. (The transition `desire_1000T_adv = false` is to show sequence for non 1000BASE-T implementations.)